

ICS 29.120.50

CCS K 31



**NATIONAL STANDARD OF THE
PEOPLE'S REPUBLIC OF CHINA**

GB 10963.1-2005

Replacing GB/T 10963.1-2005

**Electrical accessories. Circuit-breakers for overcurrent
protection for household and similar installations - Part 1:
Circuit-breakers for a. c. operation**

电气附件 家用及类似场所用过电流保护断路器 第1部分：用于交流的断路器

(English Translation)

Issued on: November 19, 2020

Implemented on: June 1, 2021

Issued by: State Administration for Market Regulation

Table of Contents

Foreword	
1 Scope	
2 Normative references	
3 Terms and definitions	
4 Classification	
5 Breaker characteristics	
6 Logo and other product information	
7 Standard working conditions used	
8 Structure and action requirements	
9 Experiment	
Appendix A (informative appendix) Method for determining short-circuit power factor	
Appendix B (Normative Appendix) Determining Electric Clearance and Creepage Distance	
Appendix C (Normative appendix) Test procedure and number of samples	
Appendix D (informative appendix) Circuit breaker and other short-circuit protection connected in the same circuit under short-circuit conditions	
Coordination of electrical appliances (SCPD)	
Appendix E (Normative Appendix) Special requirements for safety extra-low voltage auxiliary circuits	
Appendix F (informative appendix) Wiring terminal example	
Appendix G (informative appendix) Comparison of ISO and AWG copper conductors	
Appendix H (Normative Appendix) Apparatus for short circuit test	
Appendix I (Normative Appendix) Routine Test	
Appendix J (Normative Appendix) Special requirements for circuit breakers with screwless terminals connected to external copper conductors	
Appendix K (Normative Appendix) Special requirements for circuit breakers with flat quick-connect terminals	
Appendix L (Normative Appendix) Screw-type terminals for connecting external untreated aluminum wires and connecting copper or	
Special requirements for aluminum threaded terminal circuit breakers for aluminum wires	
Reference	

Foreword

GB/T 10963 "Overcurrent protective circuit breakers for electrical accessories household and similar places" is divided into the following three parts:

---Part 1: Circuit breakers used for AC;

---Part 2: Circuit breakers for AC and DC;

---Part 3: Circuit breakers for DC:

This part is Part 1 of GB/T 10963:

This section was drafted in accordance with the rules given in GB/T 1.1-2009:

This part replaces GB/T 10963.1-2005 "Electrical accessories for household and similar places with overcurrent protective circuit breakers-Part 1:

Compared with GB/T 10963.1-2005, the main technical changes are as follows:

---Added 5.2.5 Single-pole rated making and breaking capacity (I_{cn1}) rated value requirements (see 5.2.5);

---Added the single-pole rated making and breaking capacity (I_{cn1}) marking requirements (see Chapter 6);

---Increase the electrical clearance between the live parts of different poles and the live parts and some non-contact surfaces after installation can be reduced Small, but need corresponding test verification (see 8.1.3);

---Added a description between the live parts of different poles "The electrical clearance of the metal parts in the arc extinguishing chamber can be less than 1mm, and the total distance is large:

The provisions of item 1 in Table 4" (see Table 4);

---The rated voltage in the third column under "Minimum Electrical Clearance" is modified to "230/400V, 230V, 400V" (see Table 4);

---Added a description, when ferroalloy or suitably coated ferroalloy is used, it is verified by the test of 9.16 (see 8.1.4.4);

---Added that the circuit breaker should also have the wiring terminals specified in Appendix L (see 8.1.5.2);

---The power consumption requirements are added to the structure and performance requirements (see 8.13);

--- It is stipulated that various forms of wires, hard wires (single core or stranded) and soft wires, shall be tested, and the type of wires shall be specified the cross-sectional area

range of the corresponding test wire (see 9.5:2);

---Added the insulation resistance measurement of the specified auxiliary circuit, and modified the test voltage requirements (see 9.7:4);

--- The 9:7:5 test voltage value is deleted, and its content is specified in 9:7:3 and 9:7:4 respectively (see 9.7:3, 9:7:4,:2005 edition 9:7:5);

---Adjust the structure of 9:7:5, including test general requirements, impulse withstand voltage, leakage current between open contacts and insulation of open contacts the impulse voltage withstand capability of the edge and basic insulation (see 9.7:5);

--- The number of impulse withstand voltage applications is modified to "5 positive impacts and 5 negative impacts" (see 9.7:5:1);

--- If only one breakdown occurs, the number of additional shocks is modified to "10 additional shocks can be applied" (see 9.7:5:2);

---Verification of the leakage current between the open contacts has been added to verify the leakage current requirements after the test of 9:12:11:4:4 (see 9.7:5:3);

---Increase the requirement to verify the free trip function; for different trip types of circuit breakers, the upper limit value is for each pole current, and the lower limit value is for all poles connected in series conduct current (see 9.10:3);

---Add 9:12:11:4:4 "Multi-pole circuit breaker single-pole making and breaking capacity test" in the short-circuit test (see 9.12);

---For circuit breakers with rated voltage of 120V or 120/240V, the resistance of the resistor R'is changed from "7:5ohm" to "0:75ohm" (See 9.12:9:2);

--- In the resistance to abnormal heat and flame test, the parts that do not need to be tested and the parts where the glow wire cannot be directly applied are added (See 9.15);

---Updated the short circuit test circuit diagram (see Figure 3, Figure 4 and Figure 5);

---Added the graphic logo in Figure 17 (see Figure 17);

---Updated Appendix B (see Appendix B);

--- 9.15 Abnormal heat resistance and flame resistance test are independent of program A2, update test program B according to the latest 9:7, add E3 multi-pole disconnect the single-pole making and breaking capacity test of the device (see Appendix C):

The translation method used in this section is equivalent to the IEC 60898-1:2015
 ``Overcurrent protective circuit breakers for electrical accessories household and similar places Part 1: Circuit Breakers Used for AC":

The Chinese documents that have a consistent correspondence with the international documents cited in this section are as follows:

- GB/T 2900 (all parts) Electrical terminology [IEC 60050 (all parts)];
- GB/T 4208-2017 enclosure protection level (IP code) (IEC 60529:2013, IDT);
- GB/T 5023 (all parts) PVC insulated cables with rated voltages of 450/750V and below [IEC 60227 (all parts) Minute)];
- GB/T 5169.10-2017 Fire hazard test for electric and electronic products Part 10: Glow wire/hot wire basic test method Method glow wire device and general test method (IEC 60695-2-10:2013, IDT);
- GB/T 5169.11-2017 Fire hazard test for electrical and electronic products Part 11: Glow wire/hot wire basic test method Method of Glow Wire Flammability Test Method (GWEPT) (IEC 60695-2-11:2014, IDT) of finished products;
- GB/T 5465.1-2009 Graphical symbols for electrical equipment Part 1: Overview and classification (IEC 60417 Database: 2007-01, MOD);
- GB/T 13539 (all parts) low voltage fuse [IEC 60269 (all parts)];
- GB/T 14048.1-2012 Low-voltage switchgear and control equipment Part 1: General (IEC 60947-1:2011, MOD);
- GB/T 32499-2016 Aluminium wire for connecting devices for clamping parts of any material and copper wires for aluminum-based clamping parts Connection device (IEC 61545:1996, MOD);

This section has made the following editorial changes:

- Delete the notes in 5.2.5 that are irrelevant to this part;
- 9.10.2.2 The disconnection time is consistent with Table 7;
- Revise Figure 6, the original Figure 6 is missing some content;
- Deleted the abolished international standard numbers in J:10 and updated the references;

This part was proposed by China Electrical Equipment Industry Association:

This part is under the jurisdiction of the National Low Voltage Apparatus Standardization Technical Committee (SAC/TC189):

Drafting organizations of this section: Shanghai Institute of Electrical Apparatus, Zhejiang Chint Electric Co., Ltd., Shanghai Liangxin Electric Co., Ltd., Huanyu Group Zhejiang Hi-Tech Co., Ltd., Huatong Electromechanical Co., Ltd., Garcia Electronics Co., Ltd., Shanghai Noak Electric Co., Ltd., Schneider Electric (China) Co., Ltd. Shanghai Branch, Beijing ABB Low Voltage Electric Co., Ltd., Shanghai Siemens Line Protection System Co.,